

Serial No.: 10/713,310

Examiner: D. PARRIES

Title: METHOD, MEMORY MEDIA AND APPARATUS FOR DETECTION OF GRID DISCONNECT

Page 2 of 8

RECEIVED
CENTRAL FAX CENTER
NOV 05 2007**Amendments to the Claims:**

This listing of claims will replace all prior versions and listings of claims in the application.

Listing of Claims:

1. (currently amended) A method for preventing islanding in a power system that includes a power grid having a feeder connected in circuit with a distributed generator and at least one load, said method comprising:

determining a phase shift of a voltage based solely on ~~consecutive~~ sequential frequency measurements ~~over multiple periods of time~~ at an output of said distributed generator;

comparing said phase shift to a threshold phase shift that signifies a phase shift due to a disconnect of said grid from said feeder; and

if said phase shift is greater than said threshold phase shift, issuing a command for a disconnect of said distributed generator from said feeder.

2. (previously presented) The method of claim 1, wherein said phase shift is determined by a comparison at a current zero-crossing and a previous zero-crossing of said voltage.

3. (previously presented) The method of claim 2, wherein said comparison is based on a frequency f_n at said current zero-crossing and a frequency f_{n-1} at said previous zero-crossing.

4. (previously presented) The method of claim 1, wherein said phase shift is determined by:

$$\theta_n = 2\pi \cdot \left(1 - \frac{f_{n-1}}{f_n}\right)$$

where θ_n is said phase shift and f_n and f_{n-1} are the frequencies at a current zero-crossing and a previous zero-crossing of said voltage, respectively.

Serial No.: 10/713,310

Examiner: D. PARRIES

Title: METHOD, MEMORY MEDIA AND APPARATUS FOR DETECTION OF GRID DISCONNECT

Page 3 of 8

5. (previously presented) The method of claim 1, wherein said phase shift is determined by:

$$\theta_{total} = \theta_{n-2} + \theta_{n-1} + \theta_n = 2\pi \cdot \left(3 - \frac{f_{n-3}}{f_{n-2}} - \frac{f_{n-2}}{f_{n-1}} - \frac{f_{n-1}}{f_n} \right),$$

where θ_{total} is said phase shift, θ_n , θ_{n-1} , and θ_{n-2} , are the current, the first previous and the second previous phase shifts, respectively, and f_n , f_{n-1} , f_{n-2} , f_{n-3} , are the frequencies at a current, a first previous, a second previous and a third previous zero-crossing of said voltage, respectively.

6. (currently amended) A controller for preventing islanding in a power system that includes a power grid having a feeder connected in circuit with a distributed generator and at least one load, said controller comprising:

a processor, a memory and an input/output unit, wherein said memory includes a grid disconnect program that causes said processor to perform the operations of:

determining a phase shift of a voltage based solely on ~~consecutive~~ sequential frequency measurements ~~over multiple periods of time~~ at an output of said distributed generator;

comparing said phase shift to a threshold phase shift that signifies a phase shift due to a disconnect of said grid from said feeder; and

if said phase shift is greater than said threshold phase shift, issuing a command for a disconnect of said distributed generator from said feeder.

7. (original) The controller of claim 6, wherein said phase shift is determined by a comparison of a current zero-crossing and a previous a zero-crossing of said voltage.

8. (previously presented) The controller of claim 7, wherein said comparison is based on a frequency f_n at said current zero-crossing and a frequency f_{n-1} at said previous zero-crossing.

Serial No.: 10/713,310

Examiner: D. PARRIES

Title: METHOD, MEMORY MEDIA AND APPARATUS FOR DETECTION OF GRID DISCONNECT

Page 4 of 8

9. (previously presented) The controller of claim 6, wherein said phase shift is determined by:

$$\theta_n = 2\pi \cdot \left(1 - \frac{f_{n-1}}{f_n}\right),$$

where θ_n is said phase shift and f_n and f_{n-1} are the frequencies at a current zero-crossing and a previous zero-crossing of said voltage, respectively.

10. (previously presented) The controller of claim 6, wherein said phase shift is determined by:

$$\theta_{total} = \theta_{n-2} + \theta_{n-1} + \theta_n = 2\pi \cdot \left(3 - \frac{f_{n-3}}{f_{n-2}} - \frac{f_{n-2}}{f_{n-1}} - \frac{f_{n-1}}{f_n}\right),$$

where θ_{total} is said phase shift, θ_n , θ_{n-1} , and θ_{n-2} , are the current, the first previous and the second previous phase shifts, respectively, and f_n , f_{n-1} , f_{n-2} , f_{n-3} , are the frequencies at a current, a first previous, a second previous and a third previous zero-crossing of said voltage, respectively.

11. (currently amended) A memory media for a controller for preventing islanding in a power system that includes a power grid having a feeder connected in circuit with a distributed generator and at least one load, said controller comprising a processor, a memory and an input/output unit, said memory media comprising a grid disconnect detection program that causes said processor to perform the operations of:

determining a phase shift of a voltage based solely on ~~consecutive~~ sequential frequency measurements ~~over multiple periods of time~~ at an output of said distributed generator;

comparing said phase shift to a threshold phase shift that signifies a phase shift due to a disconnect of said grid from said feeder; and

Serial No.: 10/713,310

Examiner: D. PARRIES

Title: METHOD, MEMORY MEDIA AND APPARATUS FOR DETECTION OF GRID DISCONNECT

Page 5 of 8

if said phase shift is greater than said threshold phase shift, issuing a command for a disconnect of said distributed generator from said feeder.

12. (original) The memory media of claim 11, wherein said phase shift is determined by a comparison of a current zero-crossing and a previous a zero-crossing of said voltage.

13. (previously presented) he memory media of claim 12, wherein said comparison is based on a frequency f_n at said current zero-crossing and a frequency f_{n-1} at said previous zero-crossing.

14. (previously presented) The memory media of claim 11, wherein said phase shift is determined by:

$$\theta_n = 2\pi \cdot \left(1 - \frac{f_{n-1}}{f_n}\right),$$

where θ_n is said phase shift and f_n and f_{n-1} are the frequencies at a current zero-crossing and a previous zero-crossing of said voltage, respectively.

15. (previously presented) The memory media of claim 11, wherein said phase shift is determined by:

$$\theta_{total} = \theta_{n-2} + \theta_{n-1} + \theta_n = 2\pi \cdot \left(3 - \frac{f_{n-3}}{f_{n-2}} - \frac{f_{n-2}}{f_{n-1}} - \frac{f_{n-1}}{f_n}\right),$$

where θ_{total} is said phase shift, θ_n , θ_{n-1} , and θ_{n-2} , are the current, the first previous and the second previous phase shifts, respectively, and f_n , f_{n-1} , f_{n-2} , f_{n-3} , are the frequencies at a current, a first previous, a second previous and a third previous zero-crossing of said voltage, respectively.

16. (canceled)